
FX0458/1 Datasheet



Product Name // Fuseholder FX0458 Series Protection **Category PC2 Snap Fit To Panel Solder Tag Termination** 1mm-1.5mm Panel 5mm x 20mm Fuse Screw Cap Carrier **Screwdriver Release**







// Product Description:

- O Protection Category PC2 Touchproof Fuseholder
- 5mm x 20mm fuse carrier, Screw Cap, Screwdriver Release
- O Snap Fit To Panel mount, choice of panel thickness depending on part code: /1 - 1mm-1.5mm (black sleeve), /2 - 2mm-3mm (grey sleeve)
- O Solder Tag Termination
- O Insulation Boot for rear of connector available separately (part code 11327)

// General Information:

Product Display Title: Product Family:

Product Series:

Change Notes:

Approvals:

Body Material: **Current Max:**

Flamability Rating:

Function:

Fuseholder Protection Category:

Fuse Carrier:

Fuse Size:

Max Operating Temperature: Min Operating Temperature: Max Panel Thickness: Min Panel Thickness:

Voltage Max:

Protection Category PC2 Touchproof Fuseholder

Fuseholders

PC Mounting PC1, PC2 and PC3

MK-009078-SL-

CSA, UL

Polyester (PET)

10A, 16A UI 94V-0

Pc2 Fuseholder

PC2

Screw Cap/Screwdriver Release

5mm x 20mm

+85°C

-20°C 1.5mm

1mm

250V

// Product PDF Links



// Product 3D CAD Model Links



FX0458/13D CAD Model